


G3YYD's 2Tone, Operational Information



In Use

The FFT display: Tune the radio so the RTTY twin peaks and the short yellow vertical AFC tuning indicators are near or co-incident with the vertical yellow lines. The long vertical lines are at the set tone frequencies. The displayed band width can be adjusted, click on Setup button, between 449 and 1292Hz at 45.45 baud centred on the tone pair. Bandwidth at 75 bauds is 741 to 2133Hz. It has a 60dB dynamic range and updates every 85 milliseconds at 45.45 baud. Note unlike MMTTY FFT the display frequency range is not changed by AFC (Automatic Frequency Control).

Squelch: Characters are displayed when the signal to noise is 1dB or higher. An occasional character will be displayed with a noise input. It takes a while after a signal goes before the output is squelched, this is deliberate to ensure nothing is missed in any replies. When squelched, 2Tone stores the last 4 characters. On squelch opening these characters are sent to the DI followed by newly received characters. Squelch can be disabled go to menu setup, uncheck squelch item.

The Buttons: The top button selects the tone filter, which is Flutter mode is Narrow/Wide but in Normal mode is 1st and 2nd. The next button down marked Normal or Flutter selects the decoder type and the Setup button displays the setup dialogue.

The AFC (Automatic Frequency Control) is always on for best decode performance and will always lock onto a signal within 60Hz of the set tones. The status bar - the numeric display along the bottom of the 2Tone window - left hand side shows the direction and value in Hz to tune the receiver to be exactly on frequency. In practice the receiver should be tuned to within 30Hz of the given signal. The AFC will lock onto a RTTY signal that is well below the decode threshold. The short vertical lines at the top of the FFT display shows where the AFC is compared to the set mark and space frequencies. When transmitting 2Tone stops updating AFC preserving the AFC value for receive.

Signal to Noise ratio, next to the AFC value in the status bar is the measured signal to noise ratio of the decoded signal in dB. This is an average of S/N measured over several RTTY characters. The threshold to keep in mind is 10dB. Above this the error rate will be reasonable and as it drops below 10dB decode errors will increase very rapidly. Sometimes a seemingly strong signal has a poor signal to noise ratio due to some types of signal propagation. It is a good indicator of why a strong signal has poor decode. A poor quality transmit signal can also have a degraded signal to noise ratio.

NET: As the AFC is always on, it is essential that the N1MM DI, Digital Interface, setup menu has "NET off/on with RUN change ticked". If this is ticked then clicking on the Entry Window's Running box will alter the Net status display in 2Tone's status bar. Unticked (S&P) = "Net ON", Ticked (RUN) = "Net OFF". At start of N1MM it may be out of sync just click on the Run box in the N1MM entry window twice to correct.

Baud Rate: This can be selected in Set up dialogue for 45.45 (normal standard for amateur RTTY), 50 or 75.

Stop Bit Length: On the status bar fourth in from the left is a display of the received stop bit length. Ideally this should be around 32 to 34 milliseconds. However some RTTY software differs from the

G3YYD's 2Tone, Operational Information

1.5 stop bit standard. Values around 44mS and 48mS are common in contest set ups. At low signal to noise ratios, this value will move either side of the transmitted value.

Receiver AGC: This should be set to slow as fast will confuse the selective fade algorithms and cause AGC generated IMD (Intermodulation Distortion). Normal SSB AGC setting is good but not CW fast setting.

QSB: 2Tone Normal decoder has been optimised for HF use with selective fading. This is when one tone will be weaker or stronger than the other due to multipath propagation. 2Tone will copy with just one tone above the noise. However very rapid QSB often called flutter can confuse the selective fade algorithms. In this case click on 2Tone button Normal to change it to Flutter. But 2Tone will no longer be able to decode with a single tone present so set it back to Normal as soon as conditions allow.

Carrier QRM: Tuning in a carrier without any modulation and little QSB will result in no output from 2Tone, the AFC and S/N will not update. If a RTTY signal is QRM'd by a carrier on one of the tones, 2Tone will often decode the signal correctly even when it is weaker than the carrier. But do not expect miracles!

TX Audio: As AFC is always on, the TX frequency has to track the RX frequency during S&P. The use of AFSK transmit audio is preferred as long as the transmitter is suitable for SSB. Ensure the audio input of the transmitter is not overdriven. Use of tone frequencies above 1500Hz is preferred so that audio harmonics are removed by the rigs SSB filters.

TX FSK: The Pseudo FSK setting outputs a 5KHz tone on both left and right channels of the selected sound card. Tone is on for space and off for mark. A suitable detector circuit can be found at <http://www.w1hkj.com/FldigiHelp-3.20/PseudoFSK.html> but use 0.1uF in place of 0.5uF. The output connects to the FSK input of the rig. **Search & Pounce:** as the transmit frequency does not change with AFC, tune the rig so the small vertical AFC lines are co-incident with or very close to the long vertical lines. Not doing this will result in off frequency transmission.

RX Sound Card: Select the correct input and tune in a strong RTTY signal. Adjust the receiver and sound card gains so the peaks on the FFT (spectrum display) are about 90% of the maximum height of the display. The FFT has a degree of AGC (Automatic Gain Control) so that the gain settings are not critical.

Display: 2Tone checks on start up that it is within the display area of your monitor(s), if it is not it will automatically centre itself on the nearest monitor. If the 2Tone window is not visible it is because it is either behind another window on the display or has been minimised. Going to Menu Setup, Topmost on? Checking this item will put 2Tone always on top.

SO2R: More than one 2Tone can be used at the same time by using separate folders for each 2Tone. By using one 2Tone for the left DI and in the Setup dialogue to use line in left and line out left for the left rig with another 2Tone for the right DI with line in right and line out right for the right rig. This is in conjunction with wiring the left rig to the left Line in/out and right rig with the right line in/out.

Save Text: The decoded text can be saved to a file use menu File, Save Text. While saving text this menu item will be checked. To stop go again to File, Save Text and left click. The setting is lost when 2Tone is closed.

G3YYD's 2Tone, Operational Information

Technical Information

The sound card on transmit is set for 16bits at 12,000 samples per second at 45.45 baud and faster for 50 and 75 baud. The receive sample rate is 48,000 for all baud rates. On receive and transmit depending on 2Tone setup this can be for mono, left or right as per setup.

2Tone has been optimised to work with 45.45, 50 and 75 baud RTTY and has no other baud setting. Transmit is set for one start bit, 5 data bits and 1.5bit stop length. Bit timing accuracy is as accurate as the sound card sampling rate.

The receive tone filters used in 2Tone are raised cosine except for the 2nd filter selection which is a 2nd order extended Nyquist filter. The Normal 1st and 2nd filters bandwidth is set at baud rate in Hz. The Flutter narrow filter is twice baud Hz at -6dB and 2.6 times baud rate Hz at -70dB. The Flutter wide filter is twice baud rate at -6dB and three times baud rate Hz at -70dB.

The Normal decoder selective fade algorithm treats both tones separately using a threshold value derived from signal and noise amplitudes averages and then combined with the current tone amplitude. The individual mark and space tone values are combined to produce a final mark or space result for asynchronous decoding. Unlike standard FSK mark/space determination this system makes use of the absence of signal as well as the presence of signal and by treating the two tones separately and combining them together single tone copy is possible. This is sometimes called in-band diversity.

On transmit tapered cosine filtering, known as Tukey¹ windowing, is used to minimise occupied bandwidth. While the pseudo FSK mode outputs a 5KHz tone at 45.45 bauds with tone on for space bits. The start up sequence for AFSK and pseudo FSK is one character length (165mS at 45.45 baud) of space tone followed by one character length of mark tone and then a shift character appropriate to the following printable character. The start up sequence has been optimised for 2Tone type decoders (FLdigi RTTY decoder uses a similar technique) and is also suitable for MMTTY type decoders.

Configuration settings of 2Tone are stored in 2Tone.ini file in the same folder. If you delete this file programmed defaults will be used until you change them, which will then be stored in a new 2Tone.ini file. Corruption of this file can impact adversely on 2Tone.

More technical information on RTTY modulators and some of the history of technical developments can be found here: <http://w7ay.net/site/Technical/RTTY%20Demodulators>.

The version number of N1MM uses YY.MM.VV, where YY=year, MM=month & VV is issue in that month. 2Tone version control is similar YY.MMa. The "a" goes a, b, c etc for each up issue in the month. This is done to show that 2Tone version is not related to the N1MM version.

Peter Martinez, G3PLX was most helpful in guiding me on Windows and sound card programming. Rick Ellison, N2AMG help me overcoming a problem on the N1MM DI/MMTTY interface and Chen W7AY helped on Extended Nyquist filtering.

David, M7T & G3YYD@btinternet.com
10th July 2013

¹ https://en.wikipedia.org/wiki/Window_function#Tukey_window